

Quick Reference Guide



VL300 Standalone PIN Pad



- Press the cancel key on the idle screen (Receiving Mode). Choose the PIN pad type and press 1.
- 2. Select **Standalone** or **Press 2** to convert the PIN pad into a standalone.
- Select Yes on the confirmation dialog box, and the terminal will check the Ethernet connection; based on the successful connection, it will act as a standalone after reboot by entering the EPI screen.



Transactions

CREDIT SALE

- 1. Enter Transaction Amount and tap OK.
- Swipe/Insert/Tap card on Present Card screen or start typing card number for Manual Entry.
- 3. Sign and Tip if prompted.
- 4. Select receipt delivery method.

DEBIT SALE

- 1. Tap Credit until Debit is displayed.
- 2. Enter Transaction Amount and press OK.
- Swipe/Insert/Tap card on Present Card screen or start typing card number for Manual Entry.
- 4. Enter PIN and Tip if prompted.
- 5. Select receipt delivery method.

CREDIT VOID

- Tap Sale until Void is displayed. Press OK and enter password
- Select Tran Number or Card Number. If Tran Number, enter transaction number. If Card Number, enter last 4 digits of card.
- Transaction will appear on screen. Press OK to void transaction.
- 4. Select receipt delivery method.

CREDIT REFUND

- Tap Sale until Refund is displayed. Enter Refund amount and press OK.
- 2. Enter password if prompted.
- Swipe/Insert/Tap card on Present Card screen or start typing card number for Manual Entry.
- 4. Select receipt delivery method.

CREDIT PREAUTH

- 1. Tap Sale until PreAuth is displayed. Enter dollar amount and press OK.
- Swipe/Insert/Tap card on Present Card screen or start typing card number for Manual Entry.
 Select respirit delivery method
- **3.** Select receipt delivery method.

CAPTURE PREAUTH (Credit)

- **1.** Tap **Sale** until **Ticket** is displayed. Enter dollar amount, press **OK** and enter password.
- Select Tran Number or Card Number. If Tran Number, enter transaction number. If Card Number, enter last 4 digits of card.
- 3. Transaction will appear on screen. Press **OK** to Complete transaction.
- Sign and Tip if prompted.
- 5. Select receipt delivery method.



menu.

Favorites Menu

SETTLEMENT | Option to settle the current batch.

CHANGE PASSWORD | Set one general password OR

create custom passwords for settlements, voids\refunds & removing custom fee.

DOWNLOAD PACKAGE | Applies parameter changes or updates version on device.

COMM CONFIG | Configure your internet connection settings.


REBOOT | Power cycles device

REMOTE DIAGNOSTICS | Allows ISO to remotely troubleshoot the device.

PINPAD TYPE OPTION | Users can select either

"Work with VL100" or "Standalone" mode from the

Terminal Guide



- 1. Connection Icon
- 5. Hold to power down terminal
- Favorites Icon
- 6. Enter / Confirm Selection
- **3.** Main Menu
- 7. Main Menu on Keypad
- 4. Contact Support





